

SPECIFICATION SHEET





OPTION 1 (STANDARD)

FlushCanopy Remote power supply



OPTION2

Vertical wires Remote power supply No upcharge

Surface Canopy Integral power supply Upcharge applies

COVENANT PENDANT 1000

DESCRIPTION

Informed by the interlocking components of a snake's spine, Covenant is Lost Profile's contemporary take on a traditional glass chandelier.

MATERIALS

Brass, glass & aluminium

DIMENSIONS WEIGHT Diameter:1000mm (39.4") 15kg (33lbs) Height: 144mm (5.7")

LAMPING LED COLOUR TEMP Warm White 3000k LED strip 2700k Available upon request No upcharge

VOLTAGE/WATTAGE LUMENS/CRI 5250lm@90+CRI* 12V DC @ 70W *From the source

DRIVER

12V 90W 0-10V DIMMABLE

STANDARD FINISHES

BlondeBrass,AgedBrass,Dark Bronze (these finishes are waxed)

CUSTOM SURFACE FINISHESBrushedNickel, Chrome plating (Add 20%)

Clear enamel & powder coated finishes available on request (Add 10%)

MAINTENANCE

All LOST PROFILE metal surfaces are waxed. These metal surfaces are designed to age and patinate. Wear gloves when handling to avoid hand prints.

CEILING CANOPY

Option 1 - Standard: x1 Hexagonal Flush canopy (Remote) 180 x 6mm (7.1 x 0.2in).

Option 2 - Vertical Wires: x1 Flush canopy + x2 Cable glider mounts (Remote) Ø100 x 6mm (Ø3.9 x 0.2in).

Option 3 - Surface Canopy: x1 Round Surface canopy (Integral) Ø350 x 70mm (Ø13.8 x 2.8in). Upcharge applies.

COVENANT 1000 is supplied with 3 x 2000mm (78.8") suspension wires and 2000mm (78.8") of clear 2-core power cable.

Please advise us if you require longer suspension wires & power cable.

INSTALLATION

Assemblyrequired upon installing COVENANT as the glass is supplied separately to the internal substrate ring.

Allow 1 hour for installing the glass onto the ring. See installation guide for details.

DRIVERS & DIMMING

LOST PROFILE products are supplied with 0-10V dimmable LED drivers. PHASE & DALI Dimmable drivers are available for some regions, upon request. The location of the driver needs to be considered, whether in a ceiling cavity, in a wall cavity, or ideally in an accessible electrical cabinet.

FINISH GUIDE







BLONDE BRASS

AGED BRASS

DARK BRONZE





